

# How to configure a video pop-up on alarm

Last Modified on 10/06/2022 4:14 am EDT

How to configure video pop-up on alarm

## Procedure Steps

From System Administration, complete the following steps:

1. Create a Custom Alarm:
  - From the **Monitoring** menu, select **Alarms**.
  - Click [Add].
  - Give the alarm a name.
  - From the Device list, click on the device you want to link. A check mark indicates the device is selected.
  - From the Event list, select the event you want to link to the device, and then click the ">>" button to assign the device-event pair to the alarm.
  - Under the name, select the **Display Alarm**, **Active Alarm**, and **Must Acknowledge** check boxes.
  - Choose a **Priority** level for the alarm.
  - Click [OK].
  - Create a Camera Link:
    - From the **Video** menu, select **Digital Video**.
    - On the Device - Camera Links tab, click [Add].
    - From the **Device Type** drop-down, select the type of device that was configured in the Custom Alarm.
    - Select **Search Device by Panel Filter**, and then select the panel that is upstream of the hardware. A check mark indicates the device is selected.
    - Click [Next].
    - Choose the **Video Recorder** from the drop-down.
    - Double-click on the camera from the left pane to be linked. It should display in the Linked Camera(s) list.
    - Click [Save Link(s)].
    - Click [Finished].
  - Create an Alarm-Video Configuration:
    - From the **Video** menu, select **Digital Video**.
    - Select the Alarm - Video Configuration tab.
    - From the Alarm list, select the Custom Alarm configured in the step 1, and then click [Modify].
    - Select the **Automatically Launch Video Player on Alarm** checkbox
    - Select either **Live Only** or **Live and Recorded**.
    - Select **Start in Matrix Mode for Multiple Video Streams**.
    - Click [OK].

## Applies To

OnGuard (All versions)

## Additional Information

None

---